



Weld high-power transformerless electronics with point-source transduction for strength and precision. Deliver the full impact of drums and guitars. Capture stringed instruments with exacting phase. Breathe life into your vocal track. Features include hi-pass filter, attenuator and power switch. Rechargeable NiMH batteries provide current reserve. Elastic shock mount and carrying case are included. P48 (48V) phantom power is required.

Find a Dealer Near You or Buy Online Now.

[Buy Now](#)

[Click here to see what the pros are saying...](#)

[Click here for reviews...](#)

Applications

Studio Vocals, Choir, Acoustic Instrument, Guitar Cabinets, Bass Cabinets, Strings, Piano, Cymbals/Overheads.

equitek e100 Specifications

Operating Principle:	Condenser
Polar Pattern:	Supercardioid
Frequency Response:	30Hz to 18KHz
Sensitivity:	-38dBV (13mV) @ 1 Pa
Impedance:	200 ohms
Max SPL:	145dB, 1% THD, attenuator engaged
Self Noise:	20dBA
Hi-pass Filter:	80Hz, 6dB/oct
Attenuator:	20dB
Power Requirements:	P48, 8mA

Specifications are subject to change without notice.

